

NO. 10043

6. Connect leads from terminal #1 on each switch to negative (-) ground and to accessory.
7. Connect each individual accessory positive (+) lead to either the provided pigtail connected to terminal No. 2 on each switch or to terminal No. 2 directly.
8. Connect each individual accessory negative lead to the common negative ground. Be sure ALL splices are electrically sound and well insulated.
9. Now connect a Red wire (not provided) from the positive side of the battery to the ring terminal at the fuses.
10. Reconnect the positive (+) terminal to battery. If everything is off and you still see a spark when making a connection, consult a technician. This may indicate a cause for a dead battery. **WARNING: DO NOT USE A FUSE RATED OVER 15 AMPS! DO NOT ATTACH ANY WIRES TO THE REMAINING TERMINAL ON THE FUSE HOLDER!**

10043

